Weller

WXD 2020

2-Channel Solder- and Desoldering Station, 200 W (255 W)

Product no.: T0053429699N





Benefits

- Soldering and desoldering station, 2 channels with WXDP 120 and soldering iron WXP 120
- Soldering- and desoldering tools with intelligent WX technology
- Connection to external compressed air supply for high vacuum
- Energy effective: automatic stand-by mode for tools
- Patented, ESD safe glass display. Simple and fast setting of soldering parameter.

For this purpose, we recommend:



Solder fume extractors



Soldering irons



Cleaning



Pre-heating plates



Dimensions L x W x H (mm)	174 x 154 x 135
Dimensions L x W x H (inches)	6, 69 x 5, 94 x 5, 12
Weight (approx.) in kg	3.8
Voltage	230 V, 50 Hz
Power	200 W (255 W)
Channels	2
Temperature range (depends on tool) °C	
Temperature range (depends on tool) °F	
Temperature accuracy °C	±9
Temperature accuracy °F	±17
Temperature stability °C	±2
Temperature stability °F	±4
Equipotential bonding socket	Via 3,5 mm pawl socket on back of unit.
Display	255 x 128 dots / Backlighting
Air consumption l/min	35
Operating pressure in bar/psi	4,0 - 6,0 / 58 - 87
Capacity l/min	
Vacuum	max. 55 kPA (8psi)

Owning the bench









EREM

Phone: +49 (0) 7143 / 580-0 Fax.: +49 (0) 7143 / 580-108 Email: info@weller-tools.com Web: www.weller-tools.com